



BLACK BOX[®]

NETWORK SERVICES

RAS-PutIn Lite



Key Features

- ▶ Allows KVM access to any connected computer via Internet
- ▶ Total access under any OS, in BIOS mode, during boot, at Blue Screens
- ▶ Secure against unauthorised access through certificate and encryption
- ▶ No additional software necessary
- ▶ Real Power Management possible through optional IPM module

The new KVM IP Extender RAS-PutIn Lite amazes users through its easy handling. It belongs to the smallest devices of its kind and still offers a complete remote management solution with a wide range of features. Thanks to RAS-PutIn's approved KVM IP technology a fast transmission of all keyboard, video and mouse signals is guaranteed, in fact in highest video quality.

Ordering information

ITEM	CODE
RAS-PutIn Lite	KVS183A

Specifications

KVM Transmission —

- Transmission of video, keyboard and mouse signals
- Max. video resolution: 1280x1024 Pixel at 75 Hz refresh rate
- Compatible to almost all common KVM switches
- Automatic adjustment of data rate to transmission line
- Controllable over all java-capable browsers

Local Port —

- 2 x PS/2 plugs for keyboard and mouse
- HD 15 connector for monitor

Network access —

- Access via 10/100 MBit/s LAN, DSL or modem
- IP configuration with DHCP/bootp or static
- HTTP/1.1 and HTTPS (secure) web server
- Proprietary Console-Video-Protocol

Security —

- SSL encryption of all transmitted data with up to 256 bit
- Certificate management
- Logging of all important events

Serial port —

- Configuration
- External Modem
- Inline Power Module (IPM 220-L)

Further Functions —

- External power management for switching the remote server on and off possible
- Firmware-update over web interface

Technical Data —

- HxDxW: 22 x 177 x 107 mm
- Housing: coated steel
- Weight: < 500 gram
- External power supply unit: 3.3 V / 2.5 A