


1 x 16 ServSwitch Affinity Expansion Chassis

Your 1 x 16 ServSwitch™ Affinity Expansion Chassis (product code KV131A) is a new product that's not included in your ServSwitch Affinity manual dated July 2000. It's a 4-User Affinity chassis like the KV130A, KV132A, or KV134A. The only difference between it and the other 4-User models is that it comes from the factory with one 1 x 4 Port Card preinstalled in its bottom Port-Card slot, three 0 x 4 Port Cards preinstalled in its other Port-Card slots, and an Expansion Card preinstalled in its Expansion Slot. So, right out of the box, it's ready to support one user and sixteen CPUs in a daisychained system.

To place, install, operate, and troubleshoot your 1 x 16 Affinity, follow the instructions in the Affinity manual that apply to the other 4-User models listed above. Remember that your 1 x 16 Affinity unit has four video paths and can support a maximum of four independent users. *Before you interconnect two or more 1 x 16 units*, take each of the units but one and swap the slots of the 1 x 4 Port Card and one of the 0 x 4 Port Cards, so that the 1 x 4 Port Cards are in different slots on each Affinity unit. This will ensure that the users attached to the 1 x 4 Port Cards are properly assigned to different KVM numbers, so they can operate independently.

Also remember that if you want to install a set of 1 x 16 Affinity units in a ring topology (see the "Topologies" section of your manual), you'll need to temporarily remove the Expansion Cards in two adjacent units and set their BUS/RING jumpers to RING.

If there is anything you want to do with your 1 x 16 ServSwitch Affinity system that you're still not sure how to do after reading your manual and this sheet, please call Black Box Technical Support.

BLACK BOX and the  logo are registered trademarks, and ServSwitch and ServSwitch Affinity are trademarks, of Black Box Corporation.
Any other trademarks mentioned in this document are acknowledged to be the property of the trademark owners.

© Copyright 2000. Black Box Corporation. All rights reserved.

CUSTOMER
SUPPORT
INFORMATION

Order toll-free in the U.S. 24 hours, 7 A.M. Monday to midnight Friday: **877-877-BBOX**
FREE technical support, 24 hours a day, 7 days a week: Call **724-746-5500** or fax **724-746-0746**
Mail order: **Black Box Corporation**, 1000 Park Drive, Lawrence, PA 15055-1018
Web site: www.blackbox.com • E-mail: info@blackbox.com