1. Preferences



	REFERENCES 7 07/24/2003
Cat 5 UTP Link JOB1	BIT
SELECT ELFEXT T CONTRAST TIMEOUT OPTIONS MEASUREMENT U PC&PRINTER I/F	YPE S NITS
TALKSET DATE & TIME	
ŀ)
Highlight Talk	kset,
press (+).	



Press Top left button for Auto, Top middle for Manual, press (,

ہم 17<	282588800000000000000000000000000000000
Cat 5 UTP Link JOB1	
TIMEOUT OPTION MEASUREMENT	NS UNITS
TALKSET	
LANGUAGE RESTORE DEFA	ULTS
ש ר	ה

Highlight Date & Time, press (,





Display will revert to Ready Screen,

2. Cable Select



Press Cable Select

button will bring up screen, press ,

3. Cable ID





∼∼≉

Cat 5 UTP Link JOB1

Cat 5E UTP Perm

Cat 5E STP Perm

Cat 6-250 UTP Perm

Cat 6-250 STP Perm

(prop) D UTP Perm

(prop) D 120U Perm

⊕∽

Highlight CAT 5E UTP Perm,

(prop) D STP Perm

press (+),

6750

ഷ്ട്ര

TEST STANDARD

08:01 07/24/2003

-0

(NVP)

~

∽∼≉

Cat 5E UTP Perm JOB1

MISC. TYPES

ETHERNET

TOKEN BING

CUSTOM CABLE

TWISTED PAIR PERM

TWISTED PAIR BASIC

TWISTED PAIR CHANNEL

Display will revert to

previous screen, press (3)

€750



CABLE TYPE

-0

08:01 07/24/2003

Input info, press (\frown) , or Input info, press (\frown)

Highlight Cable ID icon, Press (,



Display will revert to Previous screen, Press (**5**), CABLE ID 08:06 07/24/2003 Cat 5E UTP Perm JOB1 INCREMENT CABLE ID SET CABLE ID SELECT DOUBLE ID

press (+),

Display will revert to previous screen,



001A

4. Stored Tests





Upper left corner of screen Shows zero (0) no tests stored, Press the Top middle button,



press (+)



press (+),

JOB OPTIONS ⊡o 08:12 07/24/2003 Cat 5E UTP Perm BLACK BOX
CURRENT JOB INFO ALL JOB INFO DELETE SELECTED JOBS RENAME
NEW JOB MAKE JOB CURRENT UNDO DELETE JOBS

The display will revert To the previous screen,



press (+).



Highlight Make Job Current, The display will revert to the previous screen, press (5),

5. Field Calibration



Icon, press (\leftarrow) ,



With the testers connected with the Field Calibration Adapter and Toner button On Remote Unit press, Press the Top left button,







Display will revert to Ready Screen,

7. Stored Tests





Test result TEST001 will appear



A list of Jobs will be shown Highlight a job, press (,



A list of tests will be shown, TEST0000 thru TEST0007...etc. Highlight a test and press (,